# **NETYS PL**User-friendly multi-socket protection 600 and 800 VA



#### **Function**

Compact and practical pluggable power protection integrating a larger number of sockets adapted to computer and IT peripherals in small office and home office environments, facilitating connection and tidier cabling.

#### Advantages

#### An innovative solution and superior design

- Modern design suitable for positioning over/under the desk or floor installations.
- Complementary USB port on the top for recharging mobile devices (e.g. phones, MP3, etc.).

# Adapted protection to meet all your needs 6 output sockets (French or German

standards) for easy distribution directly to your applications:

- 4 sockets protected against power cuts and overvoltages, aimed at your most sensitive applications (professional desk top systems, workstation and monitors). The back-up time (up to 30 minutes) enables standard PC tasks and configuration to be saved.
- 2 sockets protected against overvoltage alone for use with less critical applications and high absorption consumers (e.g. laser printers).

#### Easy to use

- Operating mode indicated by means of the smart LED indicator lights.
- Easy battery maintenance and replacement.
- Integrated mains input cable on the side, allowing all six sockets to be used.

#### **Strong points**

- An innovative solution and superior design
- Adapted protection to meet all your needs
- > Easy to use

#### **Conformity to standards**

- > EC/EN 62040-1, IEC/EN 62040-2
- > AS 62040.1.1, AS 62040.1.2, AS 62040.2
- > CE
- > RCM (E2376)

#### **Technology**


> VFD "offline"

#### **Certifications and attestations**





## Connections



- 1. Filtered output sockets
- 2. Inverter output sockets
- 3. LED
- 4. On/Off button
- 5. USB port to charge mobile devices
- 6. Fuse
- 7. USB serial port
- 8. Mains input cable

## Socket types





French socket

German socket

## General characteristics

• USB port to charge mobile devices.



- Compact and practical pluggable power protection.
- Modern design suitable for positioning over/under the desk or floor installations.
- 6 output sockets (French or German standards) for easy distribution directly to your applications.
- LOCAL VIEW software for local UPS monitoring.
- USB port to charge mobile devices.

# Standard communication features

- USB port for UPS management based on HID protocol.
- LOCAL VIEW software for local UPS monitoring and shutdown for Windows, Linux and MAC Osx.

# Technical data

	NETYS PL			
Model	NPL-0600-D	NPL-0600-F	NPL-0800-D	NPL-0800-F
Sn	600 VA		800 VA	
Pn	360 W		480 W	
Power (surge)	1200 VA			
Input/output	1/1			
INPUT				
Rated voltage	230 V			
Voltage tolerance	180 ÷ 270 V			
Rated frequency	50/60 Hz with automatic selection			
Mains connection	Cable with plug			
OUTPUT				
Rated voltage	230 V ±10%			
Rated frequency	50/60 Hz ±1%			
Wave form	Step wave			
Protection	Overload, significant discharge and short circuit			
Sockets	4 sockets for UPS and surge protection, 2 sockets for surge protection			
Socket standard	German	French	German	French
BATTERIES				
Туре	Sealed lead-acid maintenance free - expected life 3/5 years			
Back-up time(1)	15 min		20 min	
COMMUNICATION	'			
Interfaces	USB			
Local communication software	Local View			
UPS CABINET				
Dimensions WxDxH	220x220x123 mm			
Weight	3.6 kg		4.1 kg	
Colour	Black		White	
STANDARDS				
Safety	IEC/EN 62040-1, AS 62040.1.1, AS 62040.1.2			
EMC	IEC/EN 62040-2, AS 62040.2			
Product declaration	CE, RCM (E2376), UKCA			

(1) PC+17" LCD monitor.